

## FEATURES

RDM210 is a RMD signal amplifier with 2 universe; RDM210 is equivalent to two sets of RDM amplifier. Just connected to XLR socket, it can be used as simply as ordinary DMX signal amplifier.



### Parameters

RDM210 is a RMD signal amplifier with 2 universe; RDM210 is equivalent to two sets of RDM amplifier. Just connected to XLR socket, it can be used as simply as ordinary DMX signal amplifier.

- 1、 simultaneously amplify RDM/ DMX in 2 universe
- 2、 Optional mode: RDM or DMX
- 3、 Each input/ output port is optical-isolated
- 4、 Can be fixed on truss with clamps
- 5、 Can be installed to 1U equipment cabinet
- 6、 XLR port : 3-pin 1IN/1THRU/5OUT (X2)
- 7、 PowerCon power supply : 1IN/1OUT
- 8、 Terminate & Mode switch
- 9、 Input voltage : 100-240V AC50/60Hz
- 10、 Fuse: T1A, 250V
- 11、 Power: 5W

### Usage of button switch:

**Terminate:** Terminal matching resistance switch; Push this button to connect to the terminal matching resistance when THRU port is not connected to lighting fixture. Release the button and off terminal matching resistance when THRU port is connected to lighting fixture.

**Mode:** Operating mode option switch. Push this button to access to RDM mode. Release this button to make it work only under DMX mode. RDS will filter RDM data automatically when working under DMX mode.